



Display

# Broadcast Products Technical Bulletin 20-2004-091

DATE: May 24, 2004

SUBJECT: PARTS REGISTRATION—IC SBX-1602B-21  
REPLACES IC SBX-1602A

MODEL: **BKM-20D**  
**BKM-21D**  
**BKM-22X**  
**BKM-101C**  
**BKM-2085-14**  
**BKM-2085-20**  
**BKM-2090-14**  
**BKM-2090-20**  
*BVM-14M4DE*  
*BVM-14M4DE/R*  
*BVM-20M4DE/R*  
**BVM-8045QD**  
*BVM-9045D*  
**DMIF-1000**  
**DMIF-2000**

**DESCRIPTION**

A new SBX-1602B-21 IC is now available as service part number **8-741-602-94**.

To enhance reliability of the unit, replace the ICs in Table 1 (SBX-1602A, 8-741-602-21) with new SBX-1602B-21 ICs.

**Table 1**

Model	Board	IC
BKM-20D	BDD	IC108
BKM-21D	BD	IC108
BKM-22X	BXD	IC108
BKM-101C	BV	IC101
BKM-2085-14/20	BV1	IC101
		IC201
BKM-2090-14/20	BU	IC201
BVM-14M4DE	BV	IC101
BVM-14M4DE/R		
BVM-20M4DE/R		
BVM-8045QD		
BVM-9045D		
DMIF-1000	D1A	IC1
DMIF-2000	D2A	

SERIAL NO:

BKM-20D Up to 2,006,161  
 BKM-21D Up to 2,099,999  
 BKM-22X Up to 2,000,204  
 BKM-101C Up to 2,027,300  
 BKM-2085-14 All  
 BKM-2085-20 All  
 BKM-2090-14 All  
 BKM-2090-20 All  
*BVM-14M4DE Up to 2,013,151*  
*BVM-14M4DE/R Up to 2,110,784*  
*BVM-20M4DE/R Up to 2,110,060*  
 BVM-8045QD Up to 2,002,805  
*BVM-9045D Up to 2,004,080*  
 DMIF-1000 All  
 DMIF-2000 All

**NOTE:** The BKM board is used in BVM monitors, except for BKM-101C, which is used in PVM monitors.

*Italicized information in green applies to customers outside the United States.*

**ORDERING INFORMATION**

To order upgrades or for regional service center and parts ordering information, refer to the following document, which lists all contact telephone numbers:

DPMO02-040R

Technical Bulletin 001999000