



Display

Date: **October 6, 1997**

Subject: **NOTES ON BKM-103 INSTALLATION**

Model: **BKM-103**

Serial No: **2,000,001–2,000,899**
2,000,901–2,000,910
2,000,921–2,000,950
2,000,961–2,000,990

DESCRIPTION

When a BKM-103 option board is installed in the following units, an additional modification should be performed.

- PVM-14M4U
- PVM-14M2U
- PVM-20M4U
- PVM-20M2U

The modification enables the following enhancements.

- The remote address can now be set on the monitor menu.
- Installation of a BKM-103 option board is now recognized by STATUS area in the menu.
- CN1202 on the M board no longer comes in contact with the power block shield.

PARTS REQUIRED

Part No.	Description	Qty.
8-759-462-06	μPD78P018FYCW-S01 (IC1201)	1
1-564-507-11	4P Connector (vertical type)	1

MODIFICATION PROCEDURE

1. Replace IC1201 on the BKM-103 M board with a new ROM.
2. Solder a jumper between CN1201-8 and CN1201-12 on the M board.
3. Replace CN1202 connector on the M board with a new 4P connector.