



Display

Date: **May 15, 2000**

Model: **BVM-1310, BVM-1410C, BVM-1410P
BVM-1410PM, BVM-1910, BVM-1912
BVM-2010C, BVM-2010P, BVM-2010PD
BVM-2010PM, BVM-2012P**

Subject: **ENHANCING EA BOARD RELIABILITY**

Serial No: **ALL**

DESCRIPTION

To enhance the reliability of the EA board, change resistors R10, R11, R12, R61, and R62 as detailed in Table 1.

Table 1

Ref	Former		New	
	Part No.	Description	Part No.	Description
R10	1-247-833-00	Res, Carbon, 1.2kΩ, 1/4W	1-216-433-00	Res, Metal, 1.2kΩ, 1W
R11 R12	1-249-448-11	Res, Inflammable Carbon, 1.2Ω, 1/4W	1-216-350-11	Res, Metal, 1.2Ω, 1W
R61 R62	1-215-882-00	Res, Carbon, 22Ω, 2W	1-215-907-11	Res, Metal, 22Ω, 3W