



Display

Video Products Technical Bulletin 30-2004-039

DATE: **March 1, 2004**SUBJECT: **NO POWER**

MODEL: ***PVM-14L2***
PVM-14L2
PVM-14L2//C
PVM-14L3
PVM-14L4
PVM-14L4//C
PVM-14L5
PVM-14L5/1
PVM-20L2
PVM-20L2
PVM-20L2//C
PVM-20L4
PVM-20L4//C
PVM-20L5
PVM-20L5/1
PVM-D14L5A
PVM-D20L5A

SERIAL NO:

<i>PVM-14L2</i>	<i>2,500,001–2,500,100</i>
PVM-14L2	2,000,001–2,005,650
<i>PVM-14L2//C</i>	<i>2,800,001–2,800,100</i>
<i>PVM-14L3</i>	<i>2,000,001–2,001,320</i>
<i>PVM-14L4</i>	<i>2,000,001–2,007,164</i>
<i>PVM-14L4//C</i>	<i>2,800,001–2,800,150</i>
PVM-14L5	2,000,001–2,000,996
PVM-14L5/1	2,100,001–2,103,130
<i>PVM-20L2</i>	<i>2,500,001–2,500,050</i>
PVM-20L2	2,000,001–2,001,800
<i>PVM-20L2//C</i>	<i>2,800,001–2,800,050</i>
<i>PVM-20L4</i>	<i>2,000,001–2,003,547</i>
<i>PVM-20L4//C</i>	<i>2,800,001–2,800,050</i>
PVM-20L5	2,000,001–2,000,810
PVM-20L5/1	2,100,001–2,102,049
<i>PVM-D14L5A</i>	<i>2,000,001–2,000,466</i>
<i>PVM-D20L5A</i>	<i>2,000,001–2,000,256</i>

Italicized information in green applies to customers outside the United States.

DPMO03-057

DESCRIPTION

The monitor may not power-on if a component part on the G board (such as Q606, Q617, Q618, IC602) fails.

PARTS REQUIRED

Part No.	Description	Qty.
8-719-110-72	Zener Diode, RD30ES-T1B	1

Also Required: Sony bond SC608LVZ or equivalent

ORDERING INFORMATION

To order upgrades or for regional service center and parts ordering information, refer to the following document, which lists all contact telephone numbers:

Technical Bulletin *001999000*

MODIFICATION PROCEDURE**G Board (Side B, Zone E-2)**

- Solder a zener diode between the cathode of D627 and the ground side of C624 with its cathode connected to D627.
NOTE: This places the diode between the collector and the emitter of Q618.
- Secure the diode to the board with bond.