



Display

Date: **December 22, 1997**

Subject: **ADDITION OF 16:9 FUNCTION**

Model: **PVM-5041Q**

Serial No: **2,000,001–2,008,100**

DESCRIPTION

With the addition of the 16:9 aspect ratio function, certain changes to the machine are now in effect. (See Table 1.)

Table 1

Parts	Former	New
QB Board	A-1275-104-A	A-1275-137-A
R Chassis	4-036-721-01	4-036-721-03
Connector Ass'y	4 Pin	5 Pin
D Board	A-1346-067-A	A-1346-516-A

NOTES:

- The former QB board has been discontinued. Therefore, when replacing a former QB board with a new QB board, replace the former R chassis with a new R chassis (suffix -03) at the same time. Since CN404 on the new QB board has 5 pins instead of 4 pins, insert CN504 pins starting with pin 1 and leave pin 5 unused. (However, the 16:9 function is not available.)
- When replacing a former D board with a new D board, insert pins starting with pin 1 and leave pin 5 unused.
- When repairing units with serial numbers 2,500,001 and higher, use the new parts shown in Table 1: