

Sony Electronics Inc.
Business and Professional Products Group
Technical Publications
3300 Zanker Road, San Jose, California 95134

Display

Date: **March 11, 1996**

Subject: **CHANGE OF HEATER RESISTOR**

Model: **PVM-95/96/97/135/136/137**

Serial No: **SEE TEXT**

DESCRIPTION

Excess current flow may cause malfunction of the heater resistor. To correct this problem, replace R710 on the C board with a carbon resistor.

This information affects the following serial numbers.

| | |
|---------|---------------------|
| PVM-95 | 1,000,001–1,009,868 |
| PVM-96 | 1,000,001–1,001,750 |
| PVM-97 | 1,000,001–1,002,800 |
| PVM-135 | 1,000,001–1,002,000 |
| PVM-136 | 1,000,001–1,000,821 |
| PVM-137 | 1,000,001–1,001,300 |

NOTE: Units with serial numbers higher than those listed have been factory modified.

PARTS REQUIRED

| Part No. | Description | Qty. |
|--------------|-------------------------|------|
| 1-249-454-11 | Res, Carbon, 3.9Ω, 1/4W | 1 |