



Display

Broadcast Products Technical Bulletin 20-2003-212

DATE: **October 6, 2003**SUBJECT: **CHANGE IN CRT HEATER IMPEDANCE**

MODEL: ***BVM14M4DE***
BVM-14M4DE/R
BVM-14M4E/R
PVM-14M4A
PVM-14M4B
PVM-14M4E
PVM-14M4U

SERIAL NO: **ALL**

Italicized information in green applies to customers outside the United States.

DESCRIPTION

Heater impedance is changed in the following replacement CRTs:

CRT	CRT Lot No.
14MT1	009020001 and higher
14MT3	008240001 and higher
14MZ1	302200001 and higher
14MZ3	302200001 and higher

When you replace the CRT, replace L705 (56 μ H) on the C board with a new 68 μ H choke coil.

Replacing the choke coil sets the correct heater voltage and provides a longer CRT life.

PARTS REQUIRED

Part No.	Description	Qty.
1-406-664-11	Choke Coil, 68 μ H	1

ORDERING INFORMATION

To order upgrades or for regional service center and parts ordering information, refer to the following document, which lists all contact telephone numbers:

Technical Bulletin *001999000*

DPMO01-059R4