



# Video Products Technical Bulletin 30-2003-164

DATE: **September 1, 2003**

SUBJECT: **B, T, AND M BOARD COMPATIBILITY**

MODEL: ***PVM-14L3***  
***PVM-14L4***  
***PVM-14L5***  
***PVM-20L4***  
***PVM-20L5***  
***PVM-D14L5A***

SERIAL NO:

*PVM-14L3*     *2,000,001-2,000,655*  
*PVM-14L4*     *2,000,001-2,002,240*  
PVM-14L5     2,000,001-2,000,996  
*PVM-20L4*     *2,000,001-2,001,385*  
PVM-20L5     2,000,001-2,000,810  
*PVM-D14L5A*   *2,000,001-2,000,054*

*Italicized information in green applies to customers outside the United States.*

**DESCRIPTION**

New B and T boards are available with an improved EXT SYNC circuit. Former and new boards are not compatible.

When you replace either the B or T board:

- Replace both boards simultaneously with the board listed in Table 1.
- Replace the M board; otherwise, video may not be output. (See Table 1.)

**NOTE:** The new M board has updated firmware, which supports the BKM-126M option board.

**Table 1. B, T, and M Boards**

Board	Model	New Part No.
B	PVM-14L3	8-330-030-45
	PVM-14L4	8-330-030-51
	PVM-14L5 PVM-D14L5A	8-330-030-02
	PVM-20L4	8-330-030-63
	PVM-20L5	8-330-030-24
T	All	8-330-030-10
M	All	8-330-033-04

DPMO03-026